Time switch to manage electric utilities over time between sunrise and sunset time calculated according to the set geographical area.


Through virtual trippers it's possible to program one or more night intervals during which the load stays

Particularly suitable to light shops, luminous signs, fountains, etc.

The cover on the front of the device allows for the replacement of the depleted battery




- Wide backlit display to visualize programming, time and relay
- Container: 2 DIN modules
- Text guide
- 24-hours dial with virtual trippers
- Rear cover for battery replacement








Side view



Diagram



TIME AND MANAGEMENT

TECHNICAL INFORMATION

GENERAL CHARACTERISTICS

Power supply	V AC	230 (-15% ÷ +10%)	
Frequency	Hz	50 / 60	
Absorption	VA	6	
	W	1	
Output		1 relay in monostable change-over	
Capacity at 250 V AC	Α	16 (10)	
Battery life		5 years (Lithium battery CR 2032)	
Charge reserve (for battery replacement)		1 minute	
Switchings in case of power failure		NO	
Programming resolution for night switch OFFs		30 minutes	
Operating precision		± 1 second/day at 25℃	
Operating temperature	°C	-20 ÷ +50	
Storage temperature	$^{\circ}$ C	-10 ÷ +70	
Degree of protection		IP20	

CONNECTABLE LOADS

	_		
Incandescent	P	2000	W
Fluorescent (compensated)		250	VA
Low voltage halogen	\Box	1000	VA
Halogen (230 V~)	ф(+++)ф	2000	W
Low consumption (CFL)		200	VA
Low consumption (Downlights)	=	200	VA
Led	A	25	VA

REFERENCE STANDARDS

Compliance with Community Directives: 2014/35/EU (LVD) • 2014/30/EU (EMCD) is declared with reference to the following standards: EN 60730-2-7




....

DIGITAL TWILIGHT TIME SWITCHES

- Power supply: 230 V AC 50/60 Hz
- Available programming:
- P1 fixed with possibility of night-switch OFFs of minimum 30 minutes
- Sunrise and sunset times are calculated according to phone prefix (for Italy) or geographical coordinates
- Display of the calculated sunset and sunrise times
- Correction of sunrise and sunset times: \pm 120 minutes
- Automatic summer time update
- Manual override of the relay (temporary or permanent)
- Battery life: 5 years (replaceable just removing rear cover)
- Depleted battery signal
- Relays switching only with power supply





Code	Model	Description	n. relays
VE707600	Simply AST	Astronomical time switch with simplified programming	1



